### **Amplifier**

DA8 is a 4 channels amplifier used with all APG loudspeakers ranges depending on the desired application.

DA8 includes signal processing, analog, AES3, Dante/AES67 inputs and outputs, and a bright 4.3" IPS display with capacitive touch.

The 4 channels offers high power and voltage, allowing for high SPL even with 8 or 16  $\Omega$  loads, and is capable of delivering a massive 4 x 2000 W output on 4  $\Omega$  loads.

The amplifier's power supply has been designed to operate anywhere in the world. An internal energy storage system allows the amplifier keep a consistent performance in the event of a drop in the quality of the electrical network to which the amplifier is connected.

The amplifier can be controlled with touch screen. Available functions includes preset recall, gain, delay, and muting functions.

DA8 can also be controlled remotely with Armonía Plus software.





DA8 Amplifier

Number of channels: 4

Output power @8 $\Omega$ : 1500W per channel Output power @4 $\Omega$ : 2000W per channel Output power @2 $\Omega$ : 2500W per channel

Output power @8 $\Omega$  bridged : 4000W Output power @4 $\Omega$  bridged : 5000W

Inputs: Analog, Digital (AES3, Dante/AES67)


Remote: GPI or Ethernet


5 years warranty



# DA8

## **Technical Specifications**





DA8

#### Channel Handling

Outputs	4 x Speakon NL4
	4 Dante/AES67 TX (from local input or DSP)
Inputs	
Analog	4 XLR female
	4 XLR male (LINK)
Digital AES3	2 XLR female (4 x audio channels)
	2 XLR male (LINK)
Digital Dante/AES67	2 XLR Ethercon (4 x audio channels)

#### **Audio**

Gain	DA8
32dB	2.86 Vrms
	109 Typ dB(A)
	24 dBu
	20 Hz - 20 kHz -/- 1.0 dB
	-75 dB typ.
	20 kΩ Balanced
	65 dB typ.
	<0.1% (typical <0.05%)
er)	<0.1% (typical <0.05%)
	30mΩ
	32dB

#### **DSP**

D01		
AD converters	24 Bit Tandem™ @ 48 kHz	
	125 dB-A Dynamic Range - 0.005 % THD+N	
DA converters	24 Bit Tandem™ @ 48 kHz	
	117 dB-A Dynamic Range - 0.003 % THD+N	
Sample rate converter	24 Bit @ 96 kHz	
	140 dB Dynamic Range - 0.0001 % THD+N	
Internal precision	32 bit floating point	
Latency	2.5 ms fixed latency architecture	
Memory/Presets	50 amplifier snapshots, virtually unlimited	
	speaker presets	
Delay	2 s (input) + 100 ms (output) for time alignment	
Equalizer	Raised-cosine, custom FIR, parametric IIR:	
	peaking, hi/lo-shelving, all-pass,	
	band-pass, band-stop, hi/lo-pass	
Crossover	linear phase (FIR), Butterworth,	
	Linkwitz-Riley, Bessel: 6 dB/oct to 48 dB/oct (IIR)	
Limiters	TruePower™, RMS voltage, RMS current, Peak limiter	
Damping control	Active DampingControl™ and	
	LiveImpedance™ measurement	

#### **Display Specs**

Resolution	480x272, 4.3" diagonal
Brightness	600 nit
Control	Multitouch capacitive, Rotary encoder 20
	steps/turnwith pushbutton

#### **Output Stage**

Output otago		
per channel @ 8Ω (symmetrical) *	1500W	
per channel @ $4\Omega$ (symmetrical) $\star$	2000W	
per channel @ $2\Omega$ (symmetrical) $\star$	2500W	
per channel @ 8Ω (asymmetrical)**	1600W	
per channel @ 4Ω (asymmetrical)**	2500W	
per channel @ 2Ω (asymmetrical)**	2500W	
@ 8Ω bridged	4000W	
@ 4Ω bridged	5000W	
Maximum unclipped output voltage	160V <sub>peak</sub>	
Maximum output current	>55A <sub>peak</sub>	
*All channels driven and loaded symmetrically		
** All channels driven, but channels 2 and 4 at -6dB		

#### Power & Thermal

> 1.11.	Standby	Power	15.8 W	
	Idle	Power	33.7 W	
Idle   1/8 Power @4Ω		Power	1429 W	
		Current Draw	14.7 A <sub>ms</sub>	
		Thermal Loss	1458 BTU/h	
	Standby	Power	17.2 W	
>	Idle	Power	33.5 W	
240 V	1/8 Power @4Ω	Power	1327 W	
@		Current Draw	6.0 A <sub>ms</sub>	
		Thermal Loss	1111 BTU/h	
Power supply		Universal regulated	switch mode with PFC	
Nominal voltage (+/-10%)		100-240 VAC @ 50-60Hz		
Operating Voltage		90-264 VAC @ 50/6	90-264 VAC @ 50/60 Hz	
AC Mains connector		IEC C20 inlet (20 A	IEC C20 inlet (20 A max)	

#### Constructions

Dimensions	483 x 381 x 88.9 mm (19 x 15 x 3.5 in)
Weight	11.3 kg



